

1105

Flux Vector AC Drive



Overview

The 1105 AC drive provides reliable, efficient, cost-effective control of ordinary three-phase AC motors using either variable-frequency (V/Hz) or flux vector control. It incorporates the latest technologies in insulated gate bipolar transistors (IGBTs), pulse-width modulation (PWM), and digital signal processing (DSP) to deliver optimum motor performance, complete programmability, and simplicity of operation.

Performance Flexibility

The 1105 accommodates a broad range of performance requirements. Units may be configured for constant- or variable-torque operation or for extended torque—an economical alternative intended for centrifugal loads such as fans and pumps. The drive operates in a transducerless vector control mode that does not require a feedback device and produces full torque to base speed with full starting torque. For demanding applications, an incremental encoder or resolver and corresponding interface can be added for precise position, velocity, and torque regulation and improved dynamic performance. A dual-encoder interface is also available for position-following applications. Variable-frequency control is alternately available for applications that do not require critical velocity or torque control. Several controller options are available to meet differing application requirements.

Motor-Independent Design

The 1105 can operate any standard- or inverter-duty AC induction or synchronous motor, making it ideal for retrofits and new applications alike. A unique, proprietary digital current regulator (DCR) tunes the drive continuously in real time, eliminating the usual current-loop tuning process required by conventional drives. Digital space vector (DSV) control can be selected for reduced motor noise and low current ripple.

Auto Tuning

Once routine electrical connections have been made, simple-to-use vector-control auto-tuning features adjust virtually all motor- and load-dependent parameters. No motor maps are required. Simply enter basic motor information from the nameplate, and the advanced setup routines do the rest. The drive is completely tuned within minutes.

Application Software

A wide variety of software options is available to tailor the 1105 to an application, from a fully featured velocity/torque control for general purposes to a host of powerful programs pre-engineered for specific applications. Customization is possible with some programs using UEdit™, a Windows-based programming tool that lets users extend an application using ladder diagrams and function blocks.

Digital Setup, Easy Operation

A keypad and liquid crystal display provide a simple interface for setting and viewing operating parameters and diagnostics. All controller settings are made digitally for precision and repeatability. Readouts and fault messages are displayed in readily understandable language.

1105

Flux Vector
AC Drive

Overview **Multiaxis Operation**

(continued)

A built-in high-speed synchronous communication port allows the motion of multiple slave drives to be precisely coordinated. With optional master/slave software, the velocity ratio and position phasing of the drives can also be controlled. Multiple motors can be operated in parallel from a single drive using variable-frequency control.

Power Quality

A built-in link choke provides near-unity overall power factor and low harmonic line currents at all motor speeds. High-power units also offer a six-phase (twelve-pulse) configuration for further minimizing line harmonics in critical applications.

Protection and Advanced Diagnostics

The 1105 monitors its operating conditions and provides a comprehensive set of overload, short circuit, and other electronic protective features to ensure safe, reliable operation. Faults indications are displayed in plain language. A log maintains a history of fault occurrences.

Serial Connectivity

A fully isolated EIA RS-422/485 serial interface is provided for connecting the drive to a process controller, communication network, or programmable controller. A variety of popular communication protocols is available. An EIA RS-232 connection is also provided on 40 MHz controllers for connecting a personal computer. Optional DriveLink™ drive management software allows a network of drives to be set up, monitored, and controlled from a Windows-based personal computer.

Packaging

Compact and rugged, the 1105 is available either enclosed or as an open chassis for mounting inside an enclosure. Both versions can be foot-mounted to a wall or subplate or flange-mounted through a cutout to dissipate heat outside an enclosure.

Features & Benefits

General

- All-digital control for repeatable motor operation
- 24-bit digital signal processor (DSP) for fast, dynamic response
- 32 kilobyte battery backup memory for application setup data
- 142 kilobyte scratch pad memory and 1.5 megabyte firmware memory
- Clock/calendar maintains accurate time during power outage
- Sine-coded PWM waveform output for improved torque performance
- High-switching-frequency IGBT devices for smooth, quiet operation
- Digital current regulator for high-speed operation and fast response
- Digital space vector control for reduced motor noise and low current ripple
- Internal control loop for maintaining speed with sudden load changes
- Flux vector control for full starting torque and full torque to base speed
- Variable-frequency operation for simple control of motor speed
- Automatic field weakening for speeds up to five times base speed
- Integral DC link choke for high power factor and low total harmonic distortion
- Dynamic braking control included for fast deceleration or energy absorption
- Power loss ride-through for reducing nuisance trips
- User-programmable analog and digital inputs and outputs
- Through-hole heat sink mounting of chassis units for dissipating heat externally
- Optional NEMA 1 (IP23) and NEMA 4 (IP66) enclosures

Ease of Installation, Setup, and Maintenance

- Automated setup features require no chart recorders or meters
- Software calibration and adjustment eliminates tuning components
- Digital parameter adjustment for precise and repeatable settings
- Software input and output scaling eliminates potentiometers
- Complete, self-contained package requires minimal option boards
- Identical control boards across full power range reduces spare parts

Ease of Use

- Touch keypad for easy parameter adjustment and access to displays
- Two line descriptive plain-language display with numerical and bar graph readouts
- Comprehensive fault diagnostics displayed in plain language
- Real-time motion information and time-stamped fault log
- Optional DriveLink™ software for managing the drive from a personal computer

Safe, Reliable Operation

- Extensive electronic protection circuits
- Tolerant of AC line voltage and frequency fluctuations
- S-curve acceleration reduces shock and extends equipment life
- Multilevel security code prevents unauthorized parameter changes
- Lockout of local operator controls for safe remote operation

Specifications **Electrical**

Input Supply

Voltage:	200 to 240, 380 to 480 V AC, three-phase Phase sequence insensitive
Voltage tolerance:	-10% of minimum, +10% of maximum
Frequency:	47 to 63 Hz
Power factor:	Displacement: 1.00 at all loads and speeds Overall: 0.94 at rated load

Output Rating

Voltage:	Zero to input supply voltage, three-phase
Frequency:	Zero to 120 Hz for transducerless vector control Zero to 180 Hz for transducer-based vector control Zero to 300 Hz for variable-frequency control
Switching frequency:	20 and 40 MHz controls: Programmable from 1.9 to 12.0 kHz 16 MHz control: 6.0 kHz

Service Conditions

Efficiency:	97% nominal at rated switching frequency												
Overload current:	<table><thead><tr><th><i>Torque</i></th><th><i>Overload (1 min)</i></th><th><i>Maximum</i></th></tr></thead><tbody><tr><td>Constant</td><td>150% of rated</td><td>200% of rated</td></tr><tr><td>Variable</td><td>120% of rated</td><td>140% to 160% of rated</td></tr><tr><td>Extended</td><td>110% of rated</td><td>120% to 140% of rated</td></tr></tbody></table>	<i>Torque</i>	<i>Overload (1 min)</i>	<i>Maximum</i>	Constant	150% of rated	200% of rated	Variable	120% of rated	140% to 160% of rated	Extended	110% of rated	120% to 140% of rated
<i>Torque</i>	<i>Overload (1 min)</i>	<i>Maximum</i>											
Constant	150% of rated	200% of rated											
Variable	120% of rated	140% to 160% of rated											
Extended	110% of rated	120% to 140% of rated											

Environmental

Operating temperature:	Control section: 32° to 131° F (0° to 55° C) Heat sink: 32° to 104° F (0° to 40° C)
Storage temperature:	5° to 158° F (-15° to 70° C)
Operating humidity:	95% maximum, noncondensing
Altitude:	To 3,300 ft (1,000 m) without derating

Performance

Frequency Control (16 MHz control)

Range:	Zero to base speed at full torque Base speed to 300 Hz at constant power
Resolution:	0.20% with analog input (10-bit) 0.1 Hz with digital input

Velocity Control (20 and 40 MHz controls)

Range:	Zero to base speed at full torque Base speed to 180 Hz at constant power with transducer Base speed to 120 Hz at constant power without transducer
Regulation:	±0.001% of base speed, down to zero, with transducer ±0.5% of base speed, 2 Hz and above, without transducer

Torque Control (20 and 40 MHz controls)

Starting torque:	Constant torque: zero to 150% of rated Variable torque: zero to 120% of rated Extended torque: zero to 110% of rated
Regulation:	±3.0% of maximum with transducer ±10% of maximum without transducer

Inputs and Outputs

Analog Inputs

20 MHz control: Three (3) 12-bit analog inputs (0 to +10 V DC, ±10 V DC, and 0 to 20 mA)
16 MHz and 40 MHz controls: Three (3) 12-bit analog inputs (±10 V DC or 0 to 20 mA)
Analog Interface Module: Additional eight (8) 12-bit analog inputs (0 to +10 V DC or 0 to 20 mA)

Analog Outputs

20 MHz control: Two (2) 12-bit analog outputs (±10 V DC)
16 MHz and 40 MHz controls: Two (2) 12-bit analog outputs (±10 V DC and 0 to 20 mA)
Analog Interface Module: Additional four (4) 12-bit analog outputs (±10 V DC)

Digital Inputs

20 MHz control: Eleven (11) digital inputs (require sink of 1 mA to common)
16 MHz and 40 MHz controls: Twelve (12) digital inputs (require sink of 1 mA to common)
Converter Interface Module: Provision for input converters rated 2.5 to 28 V DC @ 30 mA, 90 to 140 V AC @ 11 mA, and 180 to 280 V AC @ 5 mA

Digital Outputs

16 MHz, 20 MHz, and 40 MHz contact I/O controls: Three (3) digital outputs (Form C contacts rated 250 V AC @ 5 A, Form A contact rated 250 V AC @ 5 A, and open-collector driver rated 24 V DC @ 500 mA)
40 MHz logic I/O control: Six (6) digital outputs (open-collector drivers rated 24 V DC @ 500 mA)
Converter Interface Module: Provision for output converters rated 5 to 60 V DC @ 3 A, 12 to 140 V AC @ 3 A, or 24 to 280 V AC @ 3 A; or for normally open or normally closed relay converters rated 250 V AC @ 8 A

